

FLEX-MIX 88

DESCRIPTION

Ultra-multifunctional audio splitter / mixer

FEATURES

- This ultra-multifunctional audio splitter / mixer is a true lifesaver that can be used in many different applications:
 - **AUDIO SPLITTER** with 2-inputs / 7-outputs (stereo input → 1 stereo + 6 mono outputs)
Possible applications are: distribution and control of audio to different zones in hotels, churches, schools, theatres, ...
 - **AUDIO MIXER** with 7-inputs / 2-outputs (1 stereo + 6 mono inputs → stereo output)
A simple but effective mixer to combine and control audio from different sources.
 - ...other combinations are possible.
- Available balanced line inputs & outputs:
 - 1 Main Stereo line input (XLR)
 - 1 Main Stereo line output (XLR)
 - 6 Mono line inputs/outputs (XLR / JACK): can be used by pair to route stereo signals!
- Each input / output section has its own volume control, pan/balance control and individual level meters.
- Compact 19" / 1U rackmount.
- Perfect for live sound, studio recording, multizone control, active speaker demo, etc



TECHNICAL SPECIFICATIONS

General : Dimensions (cm)	48 x 4.4 x 18.5 (W x H x D)
General : Weight (kg)	2.61
General : Powerinput	AC 100 - 240V, 50/60Hz
General : Energy Label	No
General : Power consumption	18
W	
General : Color	black
General : Display	none
General : Fixation	19" rack mountable
General : RU	1U
Audio : min. frequency (Hz)	20
Audio : max. frequency (Hz)	20000
Connections : input	3 pin XLR, jack, IEC
Connections : output	3 pin XLR, jack
Brand	JB SYSTEMS
EANCode	5420025684019
SKU	B08401



YOUR DEALER

