

DMX Protocol Map

LUXED S

Software Version: 1.3

BI-COLOR MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

STROBE MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K



DMX Protocol Map

LUXED 2

WALL MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

INDIVIDUAL MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer (Light 1) Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
3	0 - 255	0 - 100	Dimmer (Light 2) Closed – Open
4	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

CONTROLLER MODE			
RESET WDMX			
DMX Channel	Value	Percent	Function
1	240 - 245	-	WDMX Reset Reset Wireless DMX (keep for 3s)
WALL MODE			
DMX Channel	Value	Percent	Function
1	0 - 49	0 - 49	Mode Selection Wall Mode
2	0 - 255	0 - 100	Dimmer Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
5	1 - 99	0 - 99	Strobe Duration
INDIVIDUAL MODE			
DMX Channel	Value	Percent	Function
1	100 - 149	-	Mode Selection Individual Mode

2	0 - 255	0 - 100	Dimmer (Light 1) Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
5	1 - 99	1 - 99	Strobe Duration
6	0 - 255	0 - 100	Dimmer (Light 2) Closed – Open
7	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
8	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
9	1 - 99	1 - 99	Strobe Duration



DMX Protocol Map

LUXED 3

WALL MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

INDIVIDUAL MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer (Light 1) Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
3	0 - 255	0 - 100	Dimmer (Light 2) Closed – Open
4	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
5	0 - 255	0 - 100	Dimmer (Light 3) Closed – Open
6	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

CONTROLLER MODE			
RESET WDMX			
DMX Channel	Value	Percent	Function
1	240 - 245	-	WDMX Reset Reset Wireless DMX (keep for 3s)
WALL MODE			
DMX Channel	Value	Percent	Function
1	0 - 49	0 - 49	Mode Selection Wall Mode
2	0 - 255	0 - 100	Dimmer Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (0 - 50Hz)
5	1 - 99	1 - 99	Strobe Duration

INDIVIDUAL MODE			
DMX Channel	Value	Percent	Function
1	100 - 149	-	Mode Selection Individual Mode
2	0 - 255	0 - 100	Dimmer (Light 1) Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (0 - 50Hz)
5	1 - 99	1 - 99	Strobe Duration
6	0 - 255	0 - 100	Dimmer (Light 2) Closed – Open
7	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
8	0 - 50	0 - 50	Strobe Speed (0 - 50Hz)
9	1 - 99	1 - 99	Strobe Duration
10	0 - 255	0 - 100	Dimmer (Light 3) Closed – Open
11	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
12	0 - 50	0 - 50	Strobe Speed (0 - 50Hz)
13	1 - 99	1 - 99	Strobe Duration

DMX Protocol Map

LUXED 4

WALL MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

RANK MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer (Rank 1) Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
3	0 - 255	0 - 100	Dimmer (Rank 2) Closed – Open
4	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

INDIVIDUAL MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer (Light 1) Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
3	0 - 255	0 - 100	Dimmer (Light 2) Closed – Open
4	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
5	0 - 255	0 - 100	Dimmer (Light 3) Closed – Open
6	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
7	0 - 255	0 - 100	Dimmer (Light 4) Closed – Open
8	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

CONTROLLER MODE			
RESET WDMX			
DMX Channel	Value	Percent	Function
1	240 - 245	-	WDMX Reset Reset Wireless DMX (keep for 3s)
WALL MODE			
DMX Channel	Value	Percent	Function
1	0 - 49	0 - 49	Mode Selection Wall Mode
2	0 - 255	0 - 100	Dimmer Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
5	1 - 99	0 - 99	Strobe Duration
RANK MODE			
DMX Channel	Value	Percent	Function
1	50 - 99	50 - 99	Mode Selection Rank Mode
2	0 - 255	0 - 100	Dimmer (Rank 1) Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
5	1 - 99	0 - 99	Strobe Duration
6	0 - 255	0 - 100	Dimmer (Rank 2) Closed – Open
7	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
INDIVIDUAL MODE			
DMX Channel	Value	Percent	Function
1	100 - 149	-	Mode Selection Individual Mode
2	0 - 255	0 - 100	Dimmer (Light 1) Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
5	1 - 99	1 - 99	Strobe Duration
6	0 - 255	0 - 100	Dimmer (Light 2) Closed – Open
7	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

DMX Channel	Value	Percent	Function
8	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
9	1 - 99	1 - 99	Strobe Duration
10	0 - 255	0 - 100	Dimmer (Light 3) Closed – Open
11	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
12	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
13	1 - 99	1 - 99	Strobe Duration
14	0 - 255	0 - 100	Dimmer (Light 4) Closed – Open
15	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
16	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
17	1 - 99	1 - 99	Strobe Duration

DMX Protocol Map

LUXED 6

WALL MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

RANK MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer (Rank 1) Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
3	0 - 255	0 - 100	Dimmer (Rank 2) Closed – Open
4	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
5	0 - 255	0 - 100	Dimmer (Rank 3) Closed – Open
6	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

INDIVIDUAL MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer (Light 1) Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
3	0 - 255	0 - 100	Dimmer (Light 2) Closed – Open
4	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
5	0 - 255	0 - 100	Dimmer (Light 3) Closed – Open
6	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
7	0 - 255	0 - 100	Dimmer (Light 4) Closed – Open
8	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

DMX Channel	Value	Percent	Function
9	0 - 255	0 - 100	Dimmer (Light 5) Closed – Open
10	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
11	0 - 255	0 - 100	Dimmer (Light 6) Closed – Open
12	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

CONTROLLER MODE			
RESET WDMX			
DMX Channel	Value	Percent	Function
1	240 - 245	-	WDMX Reset Reset Wireless DMX (keep for 3s)
WALL MODE			
DMX Channel	Value	Percent	Function
1	0 - 49	0 - 49	Mode Selection Wall Mode
2	0 - 255	0 - 100	Dimmer Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (0 - 50Hz)
5	1 - 99	Jan 99	Strobe Duration
RANK MODE			
DMX Channel	Value	Percent	Function
1	50 - 99	50 - 99	Mode Selection Rank Mode
2	0 - 255	0 - 100	Dimmer (Rank 1) Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
5	1 - 99	0 - 99	Strobe Duration
6	0 - 255	0 - 100	Dimmer (Rank 2) Closed – Open
7	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
8	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
9	1 - 99	0 - 99	Strobe Duration
10	0 - 255	0 - 100	Dimmer (Rank 3) Closed – Open

DMX Channel	Value	Percent	Function
11	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
12	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
13	1 - 99	0 - 99	Strobe Duration
INDIVIDUAL MODE			
DMX Channel	Value	Percent	Function
1	100 - 149	-	Mode Selection Individual Mode
2	0 - 255	0 - 100	Dimmer (Light 1) Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
5	1 - 99	1 - 99	Strobe Duration
6	0 - 255	0 - 100	Dimmer (Light 2) Closed – Open
7	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
8	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
9	1 - 99	1 - 99	Strobe Duration
10	0 - 255	0 - 100	Dimmer (Light 3) Closed – Open
11	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
12	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
13	1 - 99	1 - 99	Strobe Duration
14	0 - 255	0 - 100	Dimmer (Light 4) Closed – Open
15	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
16	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
17	1 - 99	1 - 99	Strobe Duration
18	0 - 255	0 - 100	Dimmer (Light 5) Closed – Open
19	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
20	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
21	1 - 99	1 - 99	Strobe Duration

DMX Channel	Value	Percent	Function
22	0 - 255	0 - 100	Dimmer (Light 6) Closed – Open
23	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
24	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
25	1 - 99	1 - 99	Strobe Duration

DMX Protocol Map

LUXED 9

WALL MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

RANK MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer (Rank 1) Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
3	0 - 255	0 - 100	Dimmer (Rank 2) Closed – Open
4	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
5	0 - 255	0 - 100	Dimmer (Rank 3) Closed – Open
6	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

INDIVIDUAL MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer (Light 1) Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
3	0 - 255	0 - 100	Dimmer (Light 2) Closed – Open
4	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
5	0 - 255	0 - 100	Dimmer (Light 3) Closed – Open
6	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
7	0 - 255	0 - 100	Dimmer (Light 4) Closed – Open
8	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

DMX Channel	Value	Percent	Function
9	0 - 255	0 - 100	Dimmer (Light 5) Closed – Open
10	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
11	0 - 255	0 - 100	Dimmer (Light 6) Closed – Open
12	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
13	0 - 255	0 - 100	Dimmer (Light 7) Closed – Open
14	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
15	0 - 255	0 - 100	Dimmer (Light 8) Closed – Open
16	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
17	0 - 255	0 - 100	Dimmer (Light 9) Closed – Open
18	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

CONTROLLER MODE			
RESET WDMX			
DMX Channel	Value	Percent	Function
1	240 - 245	-	WDMX Reset Reset Wireless DMX (keep for 3s)
WALL MODE			
DMX Channel	Value	Percent	Function
1	0 - 49	0 - 49	Mode Selection Wall Mode
2	0 - 255	0 - 100	Dimmer Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (0 - 50Hz)
5	1 - 99	Jan 99	Strobe Duration
RANK MODE			
DMX Channel	Value	Percent	Function
1	50 - 99	50 - 99	Mode Selection Rank Mode
2	0 - 255	0 - 100	Dimmer (Rank 1) Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

DMX Channel	Value	Percent	Function
4	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
5	1 - 99	0 - 99	Strobe Duration
6	0 - 255	0 - 100	Dimmer (Rank 2) Closed – Open
7	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
8	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
9	1 - 99	0 - 99	Strobe Duration
10	0 - 255	0 - 100	Dimmer (Rank 3) Closed – Open
11	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
12	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
13	1 - 99	0 - 99	Strobe Duration
INDIVIDUAL MODE			
DMX Channel	Value	Percent	Function
1	100 - 149	-	Mode Selection Individual Mode
2	0 - 255	0 - 100	Dimmer (Light 1) Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
5	1 - 99	1 - 99	Strobe Duration
6	0 - 255	0 - 100	Dimmer (Light 2) Closed – Open
7	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
8	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
9	1 - 99	1 - 99	Strobe Duration
10	0 - 255	0 - 100	Dimmer (Light 3) Closed – Open
11	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
12	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
13	1 - 99	1 - 99	Strobe Duration

DMX Channel	Value	Percent	Function
14	0 - 255	0 - 100	Dimmer (Light 4) Closed – Open
15	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
16	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
17	1 - 99	1 - 99	Strobe Duration
18	0 - 255	0 - 100	Dimmer (Light 5) Closed – Open
19	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
20	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
21	1 - 99	1 - 99	Strobe Duration
22	0 - 255	0 - 100	Dimmer (Light 6) Closed – Open
23	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
24	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
25	1 - 99	1 - 99	Strobe Duration
26	0 - 255	0 - 100	Dimmer (Light 7) Closed – Open
27	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
28	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
29	1 - 99	1 - 99	Strobe Duration
30	0 - 255	0 - 100	Dimmer (Light 8) Closed – Open
31	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
32	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
33	1 - 99	1 - 99	Strobe Duration
34	0 - 255	0 - 100	Dimmer (Light 9) Closed – Open
35	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
36	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
37	1 - 99	1 - 99	Strobe Duration

DMX Protocol Map

LUXED 12

WALL MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

RANK MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer (Rank 1) Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
3	0 - 255	0 - 100	Dimmer (Rank 2) Closed – Open
4	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
5	0 - 255	0 - 100	Dimmer (Rank 3) Closed – Open
6	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

INDIVIDUAL MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer (Light 1) Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
3	0 - 255	0 - 100	Dimmer (Light 2) Closed – Open
4	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
5	0 - 255	0 - 100	Dimmer (Light 3) Closed – Open
6	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
7	0 - 255	0 - 100	Dimmer (Light 4) Closed – Open
8	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K

DMX Channel	Value	Percent	Function
9	0 - 255	0 - 100	Dimmer (Light 5) Closed – Open
10	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
11	0 - 255	0 - 100	Dimmer (Light 6) Closed – Open
12	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
13	0 - 255	0 - 100	Dimmer (Light 7) Closed – Open
14	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
15	0 - 255	0 - 100	Dimmer (Light 8) Closed – Open
16	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
17	0 - 255	0 - 100	Dimmer (Light 9) Closed – Open
18	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
19	0 - 255	0 - 100	Dimmer (Light 7) Closed – Open
20	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
21	0 - 255	0 - 100	Dimmer (Light 8) Closed – Open
22	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
23	0 - 255	0 - 100	Dimmer (Light 9) Closed – Open
24	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
25	0 - 255	0 - 100	Dimmer (Light 7) Closed – Open
26	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
27	0 - 255	0 - 100	Dimmer (Light 8) Closed – Open
28	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
29	0 - 255	0 - 100	Dimmer (Light 9) Closed – Open
30	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
CONTROLLER MODE			
RESET WDMX			
DMX Channel	Value	Percent	Function
1	240 - 245	-	WDMX Reset Reset Wireless DMX (keep for 3s)

WALL MODE			
DMX Channel	Value	Percent	Function
1	0 - 49	0 - 49	Mode Selection Wall Mode
2	0 - 255	0 - 100	Dimmer Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (0 - 50Hz)
5	1 - 99	Jan 99	Strobe Duration
RANK MODE			
DMX Channel	Value	Percent	Function
1	50 - 99	50 - 99	Mode Selection Rank Mode
2	0 - 255	0 - 100	Dimmer (Rank 1) Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
5	1 - 99	0 - 99	Strobe Duration
6	0 - 255	0 - 100	Dimmer (Rank 2) Closed – Open
7	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
8	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
9	1 - 99	0 - 99	Strobe Duration
10	0 - 255	0 - 100	Dimmer (Rank 3) Closed – Open
11	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
12	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
13	1 - 99	0 - 99	Strobe Duration
INDIVIDUAL MODE			
DMX Channel	Value	Percent	Function
1	100 - 149	-	Mode Selection Individual Mode
2	0 - 255	0 - 100	Dimmer (Light 1) Closed – Open
3	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
4	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)

5	1 - 99	1 - 99	Strobe Duration
6	0 - 255	0 - 100	Dimmer (Light 2) Closed – Open
7	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
8	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
9	1 - 99	1 - 99	Strobe Duration
10	0 - 255	0 - 100	Dimmer (Light 3) Closed – Open

DMX Channel	Value	Percent	Function
11	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
12	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
13	1 - 99	1 - 99	Strobe Duration
14	0 - 255	0 - 100	Dimmer (Light 4) Closed – Open
15	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
16	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
17	1 - 99	1 - 99	Strobe Duration
18	0 - 255	0 - 100	Dimmer (Light 5) Closed – Open
19	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
20	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
21	1 - 99	1 - 99	Strobe Duration
22	0 - 255	0 - 100	Dimmer (Light 6) Closed – Open
23	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
24	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
25	1 - 99	1 - 99	Strobe Duration
26	0 - 255	0 - 100	Dimmer (Light 7) Closed – Open
27	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
28	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)

29	1 - 99	1 - 99	Strobe Duration
30	0 - 255	0 - 100	Dimmer (Light 8) Closed – Open
31	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
32	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
33	1 - 99	1 - 99	Strobe Duration
34	0 - 255	0 - 100	Dimmer (Light 9) Closed – Open
35	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
36	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
37	1 - 99	1 - 99	Strobe Duration
34	0 - 255	0 - 100	Dimmer (Light 10) Closed – Open
35	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
36	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
37	1 - 99	1 - 99	Strobe Duration
34	0 - 255	0 - 100	Dimmer (Light 11) Closed – Open
35	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
36	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
37	1 - 99	1 - 99	Strobe Duration
34	0 - 255	0 - 100	Dimmer (Light 12) Closed – Open
35	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
36	0 - 50	0 - 50	Strobe Speed (1 - 50Hz)
37	1 - 99	1 - 99	Strobe Duration



DMX Protocol Map

LMSA-500, LMSA-1000, LMSA-1000T, LMSA-2000, LMSA-2500, LMSA-2500C

Software Version:

BI-COLOR MODE			
DMX Channel	Value	Percent	Function
1	0 - 255	0 - 100	Dimmer Closed – Open
2	0 - 255	0 - 100	Color Temperature CCT 2800K – 6500K
3	0 - 255	0 - 50	Strobe Speed 0-50Hz
4	1 - 99	1 - 99	Strobe Duration
5	0 - 100	10 - 100	Fan Speed