



## MPC1

MPC1 is a preamplifier with MP3/Bluetooth media player.

### PRE-AMPLIFIER

- Type: Media player mixer

### AUDIO SPECIFICATIONS

- Frequency response: 20 - 20000Hz @ 8 Ohm ( $\pm 0.5$  dB)
- THD+N:
- Input impedance: 10k $\Omega$  unbalance
- Signal/Noise rate: >100dB

### POWER SUPPLY STAGE

- Operating voltage/frequency: 230V (+/- 5%) 50Hz

### FUNCTIONS

- Media player: MP3/USB/SD/Bluetooth
- Tone controls input: mic/line 100 Hz, 10kHz ( $\pm 12$ dB)
- Input volume control: mic, line 1/2/3/4/aux
- Output volume control: output master

### INPUT/OUTPUT CONNECTORS

- Input signal: XLR combo (mic), pin RCA, Jack 3.5 mm
- Output signal: XLR/Jack bal. pin RCA unbal.
- Power connection: VDE

### PHYSICAL

- Dimensions (WxHxD): 485x44x130mm
- Weight: 1.7kg



## MTX84A

Stereo mixer pre- amplifier (8 IN & 4 OUT)

### PRE-AMPLIFIER

- Type: Stereo Mixer (8 input, 4 output)

### AUDIO SPECIFICATIONS

- Output level/impedance: 1V/600Ohm balanced
- Frequency response: 20- 20000Hz @ 8 Ohm ( $\pm 1$  dB)
- THD+N:
- Input impedance: 20k $\Omega$
- Signal/Noise rate: >75 (line) >60 (mic)dB

### POWER SUPPLY STAGE

- Operating voltage/frequency: 100/240V, 50/60Hz

### FUNCTIONS

- Input sensitivity: mic. 2.5 mV, line 250 mV, aux RCA 400mV
- HPF selector: 200,Hz 12dB/octave
- Tone controls input: 100 Hz, 10kHz ( $\pm 15$ dB)
- Tone controls output: 100 Hz, 10kHz ( $\pm 15$ dB)
- Phantom power: Mic 1,2,3,4, +48V

### INPUT/OUTPUT CONNECTORS

- Input signal: XLR/Jack bal. pin RCA unbal
- Output signal: XLR/Jack bal. pin RCA unbal.
- Power connection: VDE

### PHYSICAL

- Dimensions (WxHxD): 484x52x238mm
- Weight: 3.9kg