

2CH DMX DIMMER PACK

USER MANUAL



2CH DIMMER PACK USERS MANUAL

Introduction:

The 2CH DIMMER PACK has function of circuit brake protection,pre-heating,power failure memory, and control curve can be selected from switch to linear.

Please read the manual carefully before your operation. Thanks.

Parameter:

Voltage-----AC220V50/60HZ,20A

Power -----18000W

DMX Input/Output-----3Pin female XLR

Operating Instructions

1, Switch on the device: The LCD will display the current DMX address after the system automatic check (about two seconds).

2. Connect the device with any DMX signal source via 3Pin XLR wire, When the system find the DMX signal, the DMX signal indicator will fast flash, or the indicator will be dark.

3. Mode menu

A001-512:DMX address, Press UP/DOWN to set the DMX address.

P000-050:Pre-heating,Press UP/DOWN select the value between 0%-50%

D000-100:Dimming.PressUP/DOWN choose the value between 0%-100%

It should not be over the value for protecting the overload.

L/S----:CURVE MENU. Press UP/DOWN to select

L-----:Linear

S-----Switch