



ASSEMBLY INSTRUCTION

speakON STX Series | Lockable Loudspeaker Connector 4 pole Cable Connector with metal housing

IMPORTANT SAFETY INSTRUCTION

Electrical Rating acc. UL & CSA:


USR: 40A/250V, CNR: 25A/250V

Attention:

“CAUTION: NOT FOR INTERRUPTING CURRENT”

“ATTENTION: NE PAS UTILISER POUR COUPER LE COURANT”

speakON is not to be used as an AC mains or power supply connector!




Assembly of the Cable Connector

- Ⓐ Place bushing and chuck over the cable.
- Ⓑ Prepare cable as shown.
- Ⓒ Solder the wire ends to contacts of insert.
- Ⓓ Slide the chuck up the cable and align with the housing.
- Ⓔ Slide the bushing up the cable and tighten it (flat wrench SW 22mm).


Important: Align the chuck by positioning the nose into the smaller recess.

Important: Bushing must be screwed onto housing minimum 3 turns thus there is no gap between housing and bushing.

Wiring:



Wiring of the Receptacle and the Female Cable Connector:



- Ⓐ Prepare cable as shown.
- Ⓑ Insert the wires into the terminals and solder it.

NEUTRIK AG LI T: +423/237 24 24 F: +423/232 53 93
 NEUTRIK USA Inc. USA T: +1 704 / 972 3050 F: +1 704/438 9202
 NEUTRIK (UK) Ltd. UK T: +44 1983 / 811 441 F: +44 1983/811 439
 NEUTRIK Vertriebs GmbH DE/NL/AT/DK T: +49 8131 / 280 890 F: +49 8131/280 830

NEUTRIK France FR T: +33 1/4131 6750 F: +33 1/4131 0511
 NEUTRIK Tokyo Ltd. JP T: +81 3/3663 4733 F: +81 3/3663 4796
 NEUTRIK Hong Kong Ltd. HK T: +852/2687 6055 F: +852/2687 6052
 NEUTRIK India Pvt. Ltd. IND T: +91/982 05 43 424 F: +91/22 26163 540

Draft. Nr.: BDA 118 | Update: 22.11.2016 | Data subject to change without prior notice. ©2016 NEUTRIK®. ALL RIGHTS RESERVED. NEUTRIK® is a registered trademark.