ENH 2.3 MK2

DESCRIPTION

Professional multiband sound enhancer with spatial stereo processor and mono subwoofer output

FEATURES

- > This multiband sound enhancer adds harmonics to the audio, which significantly improves the definition, warmth and transparency of the music
- > Soft or Tight bass processing: improves bass punch considerably!
- > Enhancer/Exciter with multiband tuning from 1kHz to 8kHz.
- > Separate surround processor for a wider stereo experience.
- Separate mono subwoofer output with adjustable (80 → 250Hz) cutoff frequency.
- > Subwoofer phase inverter switch.
- > Balanced XLR inputs/outputs.







TECHNICAL SPECIFICATIONS

General : Dimensions (cm) $48.3 \text{ (W)} \times 4.4 \text{ (H)} \times 16.4 \text{ (D)}$

General : Weight (kg) 2.25 **General : Color** black

General : Powerinput AC 100 - 240V, 50/60Hz

General : Energy Label No
General : Power consumption W 8
General : Display none

General : Fixation 19" rack mountable

General: RU 1U
General: IP rating indoor
Audio: min. frequency (Hz) 20
Audio: max. frequency (Hz) 20000
Audio: S/N ratio (> dB) 95
Audio: max. output channels 3

Audio : functions sound effects, adjustable

Connections: input
Connections: output
Brand
EANCode
SKU

Crossover
3 pin XLR, IEC
3 pin XLR
JB SYSTEMS
5420025682138
B08213



YOUR DEALER

