

LIVE-4

DESCRIPTION

Versatile PA mixer in a handy compact format, 4 inputs / 3-channels

FEATURES

- Versatile PA mixer in a handy compact format
- 4 inputs over 3 channels (2 mic/line, 1 mono/stereo line /USB/player)
- Integrated Bluetooth receiver
- The USB connector on the top panel is Bidirectional (for stereo recording or playback via PC/Mac)
- Internal WMA, WAV, FLAC, APE and MP3 media player for USB memory sticks
- The media player can also be used as a stereo recorder
- Internal DSP-effect unit with 16 effects + separate parameter control
- HI-Z, LOW CUT and 48V Phantom power switches on the MIC/LINE channels
- Balanced Master output
- Headphones + control room output with level control
- Powered by a 5V USB C connector
- Combine it with a power bank and battery powered speakers to be 100% mobile



TECHNICAL SPECIFICATIONS

General : Dimensions (cm)	22(W) x 23(D) x 6(H)
General : Weight (kg)	1.23
General : Powerinput	USB 5Vdc
General : Energy Label	No
General : Power consumption W	5
General : Color	black
General : Display	No
General : RU	No
Audio : min. frequency (Hz)	20
Audio : max. frequency (Hz)	20000
Audio : supported audio formats	APE, FLAC, MP3, WAV, WMA
Audio : supported audio media	USB
Audio : functions	equalizer, sound effects
Connections : input	3 pin XLR, jack, usb, bluetooth
Connections : output	3 pin XLR, rca, jack
Brand	JB SYSTEMS
EANCode	5420025684071
SKU	B08407



YOUR DEALER

