

LIVE-16

DESCRIPTION

Versatile PA mixer with excellent value for money, 16 inputs / 14 channels

FEATURES

- Versatile PA mixer with excellent value for money!
- 16 inputs over 14 channels:
 - 12 mic/mono line (combo)
 - 1 mic/mono/stereo line
 - 1 mic/mono/stereo line /USB/player
- Extra CD/tape input with level control + analog recording output
- Integrated Bluetooth receiver
- The USB connector is Bidirectional and can be used for stereo recording or playback via PC/Mac
- Internal WMA, WAV, FLAC, APE and MP3 media player for USB memory sticks
- The media player can also be used as a stereo recorder
- Internal DSP-effect unit with 99 effects variations
- Each channel has:
 - Gain adjustment
 - 3-band EQ
 - 2 pre-fader aux sends
 - 1 post-fader aux/FX send
 - Pan adjustment
 - Level fader
 - Peak indicator
 - Mute switch
 - PFL switch
 - Main out routing switch
 - Group out routing switch
- Individual LOW CUT and 48V Phantom power switches on all the mono MIC/LINE channels
- Handy 7 band graphic equalizer for the main output (with IN/Bypass switch)
- Group 1/2 outputs (jack) with separate level control. Group 1/2 can also be routed directly to the main outputs.
- Balanced Main output (XLR)
- Headphones output with level control



TECHNICAL SPECIFICATIONS

General : Dimensions (cm)	63(W) x 38(D) x 12(H)
General : Weight (kg)	6.64
General : Powerinput	AC 100 - 240V, 50/60Hz
General : Energy Label	No
General : Power consumption W	35
General : Color	black
General : Display	No
General : RU	No
Audio : min. frequency (Hz)	20
Audio : max. frequency (Hz)	20000
Audio : supported audio formats	APE, FLAC, MP3, WAV, WMA
Audio : supported audio media	USB
Audio : functions	equalizer, sound effects
Connections : input	3 pin XLR, rca, jack, usb, bluetooth, IEC
Connections : output	3 pin XLR, rca, jack, usb
Brand	JB SYSTEMS
EANCode	5420025684064
SKU	B08406



YOUR DEALER

