# CLUBSPOT

## B<sub>0</sub>5506

#### DESCRIPTION

This small and lightweight 35W Led Moving head is ideal for pubs and the mobile DI!

#### **FEATURES**

- An extremely compact but very bright 35W LED moving spot with 12° beam
- The perfect solution for many applications: DJ's, parties, pubs, small clubs,...
- Very low power consumption, only 60 W!
- A real lightweight: only 3,5kg!
- 0-100% dimming and different strobe effects
- Separate gobo wheel with 7 fixed gobos + open + shaking gobos
- Separate color wheel with 7 colors + white + split colors
- Excellent built-in programs for wonderful light shows.
- Prepared for wireless DMX: just plug-in an optional WTR-DMX DONGLE
   ! (optional, Briteq® code B04645)
- Multiple working modes:
  - DMX-control: via 5, 9 or 11 channels
  - Standalone: sound activated with internal mic
  - Master/slave: wonderful synchronized lightshows.
- 4-digit LED-display for easy menu navigation







### TECHNICAL SPECIFICATIONS

**General : Application General : Dimensions (cm)**DJ & Club
28.5 x 20.5 x 16.7

General: Weight (kg) 3.33

**General : Powerinput** AC 100 - 240V, 50/60Hz

General: Energy Label No
General: Power consumption W 60
General: Color black
General: Display LED

**General : Fixation** included omega bracket

**General: IP rating** indoor

**Control : Modes** standalone, manual, DMX M/S

Control : manualYesControl : Master/SlaveYesControl : SMA RT-DMXNo

**Control : Standalone** automatic, sound

Control : programmableNoControl : upgradable softwareNoControl : maximum DMX channels11Light : lamp socketnone

**Light : Lux** 1404 lux @ 5m

Light: lumen1208Light: lampLEDLight: min. color temperature (K)9672Light: CRI82Light: mix colorsNo

**Light : functions** manual focus

Light: min. beam angle (°) 12
Light: max. beam angle (°) 12
Light: min. refresh rate (kHz) No
Light: max. refresh rate (kHz) No

**Connections : input** 3 pin XLR, IEC, usb, wireless DMX

Connections : output3 pin XLRBrandJB SYSTEMSEA NCode5420025655064







