

# HiFi RF998 User Manual

## Features:

- Noise reduction system for crystal clear sound
- Advanced 1.5" speaker for outstanding sound performance
- Double PLL system for ultimate frequency stability
- Auto mute and automatic shut-off after 10 minutes of no signal detection, conserve battery life
- Big channel-indicating logo light
- Soft leatherette ear cushions, and robust headband
- Endless headphones can be used simultaneously with one transmitter

## Keys Description



Please note this charge port is for engineering use only.

## **Button Instruction:**

**TUNE:** Press 3 seconds to turn on/off.  
Quick click to change channel.

**V+/V-:** Slide up or down to adjust volume.

**Led Light On/off:** Press “V+/V-“ button center 3seconds to turn on/off LED light.

**USB Port:** For charging only.  
Small power LED in green when charging, off when full.

**Logo:** Color changes per channel.  
CH1-RED, CH2-GREEN, CH3-BLUE

## **Specification:**

System: UHF/RF

Speaker: 1.5 inch Mylar

Impedance: 32 ohm

Frequency Response: 20-15,000Hz

S/N Ratio:  $\geq 80$ dB

Channel Separation:  $> 40$ dB

Distortion:  $< 1\%$

Power Supply: Grade-A 600mAh Rechargeable lithium battery

Work Time: About 8-10 hours

Charge Time: Less than 4 hours